


Earth rod to tape clamp




It is used to connect the horizontal electrodes type strip coil or round conductor with vertical electrodes (earth rod ref AFK0418PT).

Until 3 conductors type tinned copper strip coil can relate to an earth electrode



Delivered with a brass M10 screw



Ex - earthing system

Characteristics

Reference :	AFK0020RP
Type of installation :	Lightning earthing system
Assembly :	Clamping of the earth conductors with earth electrode $\varnothing 19\text{mm}$
Use :	Installation of lightning earthing system in compliance with NFC 17102 and NF EN 62305-3 standards
Display :	-
Conductors	Strip coil section 27x2mm to 33,5x3mm and round conductor $\varnothing 8\text{mm}$
Material :	Cupro alu
Dimensions :	54 x 42 x 20 mm
Weight :	0,150 kg
Index of protection :	-
Standards :	NF EN 62561-2

Franklin Technologie® - A full range of lightning and overvoltage protection.
In the continue framework of its products, Franklin France shall be entitled to modify specifications without notice